

## CS30-S20PO80-A12


## Capacitive Proximity Switch 3-Wire DC

Sensing range: Increased

Mind  $O \neq 0$ ,  $I \neq l \neq 1$ ,  $S \neq 5$ ,  $B \neq 8$ .

| Housing size                    | M30×1.5                  |
|---------------------------------|--------------------------|
| Mounting                        | flush                    |
| Sensing distance S <sub>n</sub> | 20 mm                    |
| Operating voltage               | 1030 V <sub>DC</sub>     |
| Reverse polarity protection     | built-in                 |
| Current consumption             | <9 mA                    |
| Current load capability         | 200 mA                   |
| Output function                 | ∠ normally open          |
| Output polarity                 | PNP                      |
| Short circuit protection        | built-in, self-resetting |
| Voltage drop                    | <2 V @ 200 mA            |
| Switching frequency             | 100 Hz                   |
| Adjustment                      | multi-turn potentiometer |
| Operating temperature           | −20+70 °C · −3+159 °F    |
| Protection class                | IP 67                    |
| Sensing face material           | PBT                      |
| Housing material                | brass                    |
| Switching indicator             | built-in                 |
| Connection                      | male connector M12       |
| Complies with                   | C€, RoHS RoHS compliant  |








**Warranty** Our products are manufactured to stringent ISO 9001 European standards to ensure that our customers only receive the best quality.



## Wiring diagram



## Pinout





Caution! This device shall not be used if the safety of persons rely on its faultless function.

XECRO reserves the right to make minor changes without prior notification.