Catalog 9EM-TK-190-3

Basic 3/8" Body

= "Most Popular"

71.5 SCFM (33.7 dm³/s)

80.5 SCFM (38.0 dm³/s)

88.0 SCFM (41.5 dm³/s) 0 to 60 PSIG (0 to 4.1 bar)

300 PSIG (20,7 bar)

1/4, 3/8, 1/2


1.7 (0.77)

1/4

0 to 125 PSIG (0 to 8.6 bar) 0 to 250 PSIG (0 to 17.2 bar)

32° to 150°F (0° to 65.5°C)

Regulator R16





R16-02-000

Features

- Non-Rising Adjustment Knob with Friction Lock Knob
- Standard with Two Full Flow 1/4" NPT / BSPT-Rc Gauge Ports
- · Panel Mount Nut
- High Flow Capacity
- Balanced Valve Design for Excellent Regulation Characteristics

Body Zinc Bonnet PBT Diaphragm Nitrile / Zinc Panel Nut Acetal Seals Nitrile Springs Steel Valve Assembly Brass / Nitrile / Acetal

NPT / BSPP-G

NPT / BSPT-Rc

Inlet pressure 100 PSIG (6.9 bar), Secondary pressure 90 PSIG (6.2 bar).

lb. (kg)

Materials of Construction

Specifications
Flow Capacity

Adjusting Range Pressure

Maximum Supply Pressure

Operating Temperature

Gauge Port (2 ea.)

Port Size

Weight

CAUTION:

1/4

3/8

1/2

WARNING


Product rupture can cause serious injury.

Do not connect regulator to bottled gas.

Do not exceed maximum primary pressure rating.

REGULATOR PRESSURE ADJUSTMENT – The working range of knob adjustment is designed to permit outlet pressures within their full range. Pressure adjustment beyond this range is also possible because the knob is not a limiting device. This is a common characteristic of most industrial regulators, and limiting devices may be obtained only by special design. For best performance, regulated pressure should always be set

by increasing the pressure up to the desired setting.



NOTE: 1.31" Dia. (33.3 mm) hole required for panel nut mounting.

Dimensions

Models Inches (mm)	А	В	С	D	£	F	G	н
Standard Unit	2.99	2.59	3.99	1.20	5,19	1,29	-	1.02
R16-XX-000	(76)	(66)	(101.3)	(30.5)	(132)	(33)		(25.9)
With Gauge	2.99	2.59	3.99	1.20	5.19	1.29	2.80	1.02
R16-XX-G00	(76)	(66)	(101,3)	(30.5)	(132)	(33)	(71)	(25.9)



B110

Pneumatic Division Richland, Michigan www.wilkersoncorp.com