116213-00



AMETEK


LAMB ELECTRIC

DESCRIPTION

- Two stage
- 240 Volts
- 5.7"/145 mm diameter
- Double ball bearings
- Single speed
- Tangential bypass discharge
- Thermoset fan end bracket
- Aluminum commutator bracket

DESIGN APPLICATION


- Equipment operating in environments requiring separation of working air from motor ventilating air
- Designed to handle clean, dry, filtered air only




SPECIAL FEATURES

Model:

- Suitable for 240 volt AC operation, 50/60 Hz
- UL recognized, category PRGY2 (E47185)
- Provision for grounding
- Skeleton-frame design
- Epoxy painted fan case
- The Lamb Electric vacuum motor line offers a wide range of performance levels to meet design needs



tes	test data is corrected to standard conditions of 29.92 Hg, 68° F.)										
	Orifice	Amps	Watts	RPM	Vac	Flow	Air				
	(Inches)		(In)		(In.H2O)	(CFM)	Watts				
	2.000	4.9	1127	19180	3.6	99.1	42				
	1.750	4.9	1141	19210	6.1	98.5	71				
	1.500	4.9	1144	19020	10.8	94.9	120				
	1.250	5.0	1144	18970	18.9	87.3	194				
	1.125	5.0	1152	18950	25.0	81.1	238				
	1.000	5.0	1159	19050	32.9	73.2	283				
	0.875	4.9	1139	19260	41.3	62.6	304				
	0.750	4.7	1110	19600	50.8	50.9	304				
	0.625	4.5	1018	20290	60.3	38.4	272				
	0.500	4.2	972	21140	68.6	26.1	210				
	0.375	3.8	895	22040	76.2	15.6	140				
	0.250	3.5	840	23210	84.4	7.6	75				
	0.000	3.4	801	24160	97.4	0.0	0				




Orifice	Amps	Watts	RPM	Vac	Flow	Air
(mm)		(ln)		(mm H2O)	(L/Sec)	Watts
48.0	4.9	1133	19193	119	46.7	55
40.0	4.9	1143	19077	239	45.3	105
30.0	5.0	1148	18959	565	39.6	218
23.0	4.9	1144	19208	996	30.8	299
19.0	4.7	1108	19614	1295	23.9	303
16.0	4.5	1022	20262	1522	18.4	273
13.0	4.2	977	21055	1721	12.9	216
10.0	3.9	907	21905	1907	8.1	151
6.5	3.5	843	23152	2133	3.8	78
0.0	3.4	801	24160	2474	0.0	0

Note: Metric performance data is calculated from the ASTM data above.

^{*} Data represents performance of a typical motor sampled from a large production quantity. Individual motor data may vary due to normal manufacturing variations.

PRODUCT BULLETIN 116213-00



IMPORTANT NOTE: Pictorial and dimensional data are subject to change without notice. Contact factory for current revision levels.

WARNING - When using AMETEK Lamb Electric bypass motors in machines that come in contact with foam, liquid (including water), or other foreign substances, the machine must be designed and constructed to prevent those substances from reaching the fan system, motor housing, and electrical components. Lamb Electric vacuum motors other than hazardous duty models should not be applied in machines that come in contact with dry chemicals or other volatile materials. Failure to observe these precautions could cause flashing (depending on volatility) or electrical shock which could result in property damage and severe bodily injury, including death in extreme cases. All applications incorporating Lamb Electric motors should be submitted to appropriate organizations or agencies for testing specifically related to the safety of your equipment.

AMETEK/Lamb Electric Division 627 Lake Street Kent, Ohio 44240 U.S.A. Tel: (330) 673-3451 Fax: (330) 673-8994 Ametek GmbH P. O. Box 1251 D-71667 Marbach Germany

Phone: + 49-714-484-9512 Fax: + 49-714-484-9513 AMETEK/Singapore Private Limited 10 Ang Mo Kio Street 65 # 05-12 Techpoint Singapore 2056 Tel: + 65-484-2388

Fax: + 65-481-6588

Issued: March, 1998