# ENGINE CONTROL AND PROTECTION DEVICE

TYPE DIP-061



## MADE TO:

## PROTECTING with stoppage or alarm indication only in case of anomaly for:

- insufficient oil pressure
- over-temperature
- belt breakage
- minimum fuel level
- air filter clogging
- cooling liquid low level
- over speed
- under speed

## DISPLAYING the following functions on the dashboard:

- hour counter
- oil pressure gauge
- oil or water thermometer
- tachometer
- fuel level gauge
- protections intervention
- protections exclusion
- battery and oil lights
- periodic maintenance request
- emergency stop

Mounting also on the machine.

Suitable for stopping both with solenoid valve and with electromagnet, for engines equipped with charge alternators, both with pre-excitation and with permanent magnet.

BY SIMPLY STARTING, IT AUTOMATICALLY CONTROLS THE ENGINE. ALL THE OTHER FUNCTIONS ARE EASY TO USE WITH JUST PRESSING THREE PUSH-BUTTONS.

Tel. +39 0521/772021 Fax +39 0521/270218 E-mail: info@elcos.it - HTTP://www.elcos.it

**ITALY** 

## **BRIEF INSTRUCTIONS**

## START KEY (FOR EXTERNAL MOUNTING)



- OFF
- MANUAL STOP
- RESET



- SUPPLY DEVICE
- CHECK VISUAL INDICATORS
- PROGRAMMING




- START ENGINE

AFTER STARTING (THE ENGINE PROTECTS ITSELF AUTOMATICALLY)
ACCESS TO THE OTHER DEVICE FUNCTIONS IS POSSIBLE
VIA A SIMPLE THREE PUSH-BUTTON OPERATION.







FOR SOME PROTECTIONS IT IS POSSIBLE TO SELECT TWO DIFFERENT TYPES OF INTERVENTION:

- ALARM. VISUAL INDICATION AND STOP
- VISUAL INDICATION AND ALARM ONLY

See pages 3 - 4 for programming

## OPERATION

#### **OIL AND BATTERY LIGHTS**



SWITCH ON WITH KEY TURNED TO "AUT" THEY SWITCH OFF WHEN ENGINE IS RUNNING WITH OIL PRESSURE AND BATTERY RECHARGE SYSTEM REGULAR

#### **ENGINE PROTECTIONS ENABLING**

The engine protections are enabled in three ways


- immediately for over speed.
- 10 seconds after threshold is passed (see page 4:INTERVENTION THRESHOLDS ADJUSTMENT) for under speed The under speed and over speed are detected by the "W" terminal extracted from the battery charge alternator (see pages 5).
- 20 seconds after the start pulse, indicated by the switching on che PROTECTIONS ACTIVE light and, in any case, 1 minute from turning key to "AUT", for anomaly probes: indicated by the switching on of the PROTECTIONS ACTIVE

(O.J.)

(P<del>LS</del>)

- TEMPERATURE PROBES:

**THERMOSTAT** 



- OIL PRESSURE SWITCH (insufficient engine oil pressure)
- COOLING LIQUID LEVEL SWITCH (cooling liquid low level)
- **FUEL SWITCH**
- •fuel reserve flashing signal (without enginestop)
- ·signal always on: stop can be programmed for minimum fuel level
- BATTERY CHARGE ALTERNATOR (battery recharge failure)
- AIR FILTER SWITCH (clogged air filter)
- **GENERIC ANOMALY**

## PROGRAMMING


All protections are programmed to stop the ENGINE.

By operating the following programmings it is possible to easily change the INTERVENTION THRESHOLDS for OVER-TEMPERATURE, OVER SPEED, UNDER SPEED and to select two different types of protection intervention (PROGRAMMABI F STOPS):

- Alarm, visual indication and stop

- Alarm and visual indication only, for UNDER SPEED, COOLING LIQUID LOW LEVEL, FUEL LOW LEVEL, BATTERY RECHARGE FAILURE (belt breakage), CLOGGED AIR FILTER AND ENGINE GENERIC ANOMALY (free).

The protections for INSUFFICIENT OIL PRESSURE or for OVERTEMPERATURE detected by thermostat (not by transmitter) produce immediate and memorized interventions with stop, it is not possible to programme them.



until the lights switch on

until the lights switch off

Keep the push-button pressed

previous steps using the push-button END OF PROGRAMMING


Turn the key to "ZERO" and then reinsert

the connector (see page 3).

When programming has been completed, check

that the set values are correct by going over the

- STOP



BATTERY RECHARGE FAILURE (belt breakage

CLOGGEĎ ÁÍŘ FILTE

GENERIC ANOMALY

**GB** DIP-061 /1

Intervention with 5 second delay

RESTORING: is obtained by turning

and memorized with


programmable stop


the start key to "ZERO"

NO STOP HO

## WIRING DIAGRAM

## **RECOMMENDED COLOURS**





#### **ACCESSORIES AVAILABLE ON REQUEST**

- (1) START KEY
- (2/7) ELECTROMAGNET OR SOLENOID VALVE
- (3) OIL PRESSURE SWITCH
- (4) TEMPERATURE SWITCH
- (18) FUEL FLOAT FOR INDICATOR AND RESERVE
- (97) OIL PRESSURE TRANSMITTER
- (112) TEMPERATURE TRANSMITTER
- (155) COOLANT LEVEL PROBE
- (26) PERMANENT MAGNET CHARGE ALTERNATOR
- (27) REGULATOR ALTERNATOR
- (28) PRE-EXCITATION CHARGE ALTERNATOR
- (40) STARTING MOTOR
- (41) BATTERY
- (157) GENERAL ALARM LIGHT
- (150) AIR FILTER CLOGGING SWITCH
- (169) EMERGENCY STOP

4 GB DIP-061 /1


## TACHOMETER ADJUSTMENT


Bring the engine up to a constant working speed and at a noted value (e.g. using a portable tachometer).


To aid the regulation it is possible to see the decimal (for 1 minute) every time the "tachometer" is selected.



Use the relevant push-button to select the TACHOMETER instrument. A number other than zero must be visible on the display. (If this is not the case, do not perform any adjustments but check the plant thoroughly).







5

PROGRAMMED FUNCTIONS CHECK				
To check the OVER-TEMPERATURE, OVER SPEED and UNDER SPEED intervention thresholds and to check which anomalies do not stop the engine, keep the push-button pressed and press the push-button at the same time, each time this last push-button is pressed, the type of function checked, in the order shown below, changes (shown by the corresponding light).				
OVERTEMPERATURE  RPM  RPM	UNDERSPEED  RPM  RPM	During this check the switching on of		
OVERSPEED  RPM  RPM	COOLING LIQUID LOW LEVEL  MINIMUM FUEL LEVEL  BATTERY RECHARGE FAILURE  CLOGGED AIR FILTER  GENERIC ANOMALY	the light, indicates that the protections are programmed for DO NOT STOP		
	OPERATION			
ENGIN	NE PROTECTIONS EXCLUSION ——			
The push-button excludes the engine stop for the protections				
	— ENGINE STOP ————	1		
The device orders stoppage in three ways:  - by turning the start key to "ZERO"  - on protection intervention  - for external emergency intervention  The device is suitable for two different stop systems (during which the light STOP is on):  - activating the ELECTROMAGNET for 20 seconds, which pulls the STOP lever  - cutting off the supply to the SOLENOID VALVE, which closes the Diesel passage				
	— MAINALARM ————			
This can be obtained by mounting a visual and/or acoustic indicator externally, connected to the relevant output. It is activated on any protection intervention.  RESET: by turning the start key to "ZERO".				
	- INSTRUMENTS			
The device incorporates five instruments (indicated by the relative lights in the form of an arrow), which can be individually selected on the DISPLAY for the following sizes:  - total working hours - engine oil pressure - engine oil and water temperature - engine speed - fuel level percentage  (INDICATOR)  Transmitters fitted on Engine for the following sizes:  (PRESSURE GAUGE)  (PRESSURE GAUGE)  (THERMOMETER)  (TACHOMETER)  (INDICATOR)  (INDICATOR)				
The TACHOMETER is displayed when the key .	("AUT") is inserted, or if called up by the SELECT INS	TRUMENTS buttor		
of the instrument.  The hour counter memoria	In the engine running, the light $\bigcirc \underline{\mathbf{h}} \succeq \underline{\mathbf{p}}$ pulses, to indictive the working hours even when the battery is disconsETER, TACHOMETER, FUEL LEVEL INDICATOR the d.	nected.		
	PERIODIC MAINTENANCE			
When it is necessary to perform the periodic		lights up.		

## **EMERGENCY STOP**

It can be obtained in all functioning conditions, mounting one or more release-type buttons. It is indicated by the visual signal ( ).

6 GB DIP-061 /1



## PROTECTION DEVICE TYPE DIP-061

Used only to survey a diesel engine while operating, commanding stopping if there are anomalies in the parts controlled by the probes.

Designed to be installed inside dashboards, electric panels, etc....

## **NOTICES**



## Warning: adhere closely to the following advice

- Always install under other equipment which produces or spreads heat.
- Always follow the Wiring Diagram on page 4-5 when making connections.
- Check that the line loading and the consumption of the connected equipment are compatible with the technical characteristics on page 8.
- All technical interventions must be performed with the engine stationary and terminal 50 of the starter motor disconnected.
- Never disconnect the terminals of the battery with engine running.
- Never use a battery charger for the emergency start-up, this could damage the equipment.
- To protect the safety of persons and the equipment, before connecting an external battery charger, disconnect the electrical plant terminals from the battery poles.

NOTE:

THE HOLE IN THE CASING USED TO INSTALL THE EQUIPMENT COULD INFLUENCE THE LEVEL OF PROTECTION. STEPS MUST BE TAKEN TO MAINTAIN THE ORIGINAL LEVEL OF PROTECTION.

#### THIS DEVICE IS NOT SUITABLE FOR OPERATING IN THE FOLLOWING CONDITIONS:

- Where the environmental temperature is outside the limits indicated in the Technical Data on page 8.
- Where there are high levels or heat from radiation caused by the sun, ovens or the like.
- Where there is the risk of fire or explosions.
- Where the device can receive strong vibrations or knocks.

## **ELECTROMAGNETIC COMPATIBILITY**

This protection device functions correctly only if inserted in plants which conform with the CE marking standards; it meets the exemption requirements of the standard EN50082-2 but it cannot be excluded that malfunctions could occur in extreme cases due to particular situations.

The installer has the task of checking that the disturbance levels are within the requirements of the standards.

## CONDUCTION AND MAINTENANCE

The following maintenance operations should be performed every week:

- check that the indicators function;
- check the batteries:
- check that the conductors are tight, check the condition of the terminals.


UNLESS WE MAKE A WRITTEN DECLARATION STATING THE CONTRARY, THIS PROTECTION DEVICE IS NOT SUITABLE FOR USE AS A CRITICAL COMPONENT IN EQUIPMENT OR PLANTS RESPONSIBLE FOR KEEPING PERSONS OR OTHER LIVING BEINGS ALIVE

YOUR ELECTRICAL TECHNICIAN CAN ASK US ANYTHING ABOUT THIS PROTECTION DEVICE BY TELEPHONING ONE OF OUR TECHNICIANS


**GB** DIP-061 /1 7

## DIMENSIONS

## TECHNICAL DATA







_	BAT	TERY	<b>SUPPLY</b>
	VOL	<b>TAGE</b>	

12 or 24 V

- CIRCUIT LOADING WITH KEY AT ZERO 10mA

- YELLOW (STOP) OUTPUT 5 MAX. CURRENT

3A

- RED/GREEN (MAIN ALARM) OUTPUT 7 MAX. CURRENT

- TEMPERATURE RANGE

3A

-10 ÷ +60 °C

- HOUR-COUNTER

4 DIGITS

- ENGINE OIL PRESSURE GAUGE

0 ÷ 7 bar

- ENGINE OIL / WATER THERMOMETER

+ 20 ÷ +145 °C

- TACHOMETER

4000 rpm

- PROTECTION LEVEL DASHBOARD / REAR

IP65 / IP20

- WEIGHT

600 g

## ORDERING DATA

### **ACCESSORIES SUPPLIED**

Type **DIP-061 12 V** code 02.66.13

 CABINET SOCKET PMO-170

code 80.42.70

Type **DIP-061 24 V** code 02.66.14

 CABINET SOCKET PMO-172

code 80.42.72

## **CONFORMITY DECLARATION**



The company Elcos s.r.l. assumes full responsibility for declaring that the equipment:

tvpe

**DIP-061** 

used in the ways and for the purposes described in the instruction and user manual is in conformity with the directive:

- 2004/108/CE

related to the electromagnetic compatibility and that repeals

the directive 89/336/CEE.

because it is built and functions in accordance with the harmonized Standards: EN61326-1, EN61326/A1, EN61000-4-2, EN61000-4-4, EN61000-4-6, EN60529.



Parma, 23/01/2009 President

Walter Consigli